


Group Control Single Color DALI DT6 Rotary Dimmer Switch

09.2410RG.04013




**Important:** Read All Instructions Prior to Installation


Function introduction




Front side



Back side



With plastic frame



With glass frame

Product Data

Output	DALI signal
Power Supply	Supply By DALI Bus
Operation Current	4mA
Operating temperature	0-40°C
Relative humidity	8% to 80%
Dimensions	80 x 80 x 20.8 mm

- Comply to DALI standard protocol IEC 62386-102, IEC 62386-207 and in compliance with DALI products from other international incorporation.
- DALI bus powered, one channel DALI bus can install multiple dimming controllers.
- No external power supply which is provided by DALI bus. Consumption current is 4mA.
- Enable to select and control 1 DALI group
- Enable to control all devices on the DALI circuit through broadcast
- Plastic or glass front plate optional
- Backlighting design to indicate the dimming status

Safety & Warnings

- DO NOT install with power applied to device.
- DO NOT expose the device to moisture.

**1. Do wiring according to connection diagram correctly.**

- This DALI rotary dimmer enables dimming commands to be sent to One Group of devices on the DALI circuit by one Group of button. A rotary switch on the back is used to select Group you would like to control and set the starting Group number, and total 16 Groups (0-15) can be selected.

- For example: Rotary switch arrow at 1, it controls Group 0 of devices. Rotary switch arrow at 15, it controls Group 14 of devices.

Rotary Switch Position	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
DALI Group for the controller	Broadcast	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14